


SQUARE
PERFECT



Make every picture perfect



SP160 VARIABLE POWER
STUDIO FLASH SET
with
19" X 26" X 17" SOFT BOX/
BARN DOOR and GEL SET

SP160 Flash Studio Kit

Thank you for your purchase of the SP160 Flash Softbox Studio kit. This manual has been written to help you with the assembly, operating procedures and accessories. Square Perfect's SP160 Flash Kit is manufactured with the finest material available. Your flash kit will provide many years of quality service with proper care and handling.

Please read this manual carefully before use, and keep it handy for use during break down of equipment. Please read and heed all safety precautions listed in this manual. For ordering spare bulbs or replacement parts, contact us at info@squareperfect.com. Also check out our extended line of photo equipment now available.

Flash Studio Kit Includes:



Nylon Carry Case. Compartmentalized for easy use



1x2 SP160 lamp body.
12' power cord.



1x2 SP803 professional duty adjustable light stand.
Stand extends from 5' to 14'.



Electronic radio trigger / receiver with sync cord and adaptors.



1x2 Four panel softbox set.
1x2 SP 4" lamp connector.

Technical notes for use:



Four leaf barn door set with color filter attached to the SP160 flash head on the SP803 stand.




1 Four leaf barn door.



1 set Red, blue, yellow frosted and honeycomb filter.



Remove protective cover from mounting tip before attempting to place flash head on stand.




1. Swivel screw.
2. Umbrella rod mount.
3. Mounting screw


SP160 Lamp Head Operation:



1. On/Off electric supply.
2. Variable flash dial.
3. On/Off, model lamp.
4. On/Off flash ready beep.
5. Flash test.
6. Sync receptacle.
7. Safety fuse.



8. Charging lamp.
9. Flash ready lamp.
10. Slave dome



11. Flash ring
12. Model lamp

Specifications:

Power Input : AC110-130 volt, 60 Hz
 Flash Power : 160ws (joule) in full
 Guide No. : 120ft/36m ISO100
 Color Temperature : 5600K
 Flash-Tube Lifetime : over 8,000 typical flashing
 Flash Power Setting : 1/16 to full
 Recharge Time : 0.5-3 seconds in full
 Flash Duration : 1/600 sec.; 1/1000 sec.
 Slave Range : 35ft /10m
 Lighting Range : 55 degree
 Modeling Power : Halogen 75w
 Bulb Base : E-14 screw
 Synch Voltage : 5 volt
 Fuse : 5A
 Dimension : 4" x 7-1/2"
 Weight : 1.8 Lb (800g)

SAFETY PRECAUTIONS:

- Become thoroughly familiar with this product before use. Run through at least one practice assembly and breakdown before you schedule a shoot.
- Make sure that the main voltage corresponds to that stated on the SP160 lamp. Account for number of lamps in use.
- Never leave the lighting unsupervised when in use. Keep children or incompetent persons away from lighting equipment.
- If the lamp or the cord show sign of wear or damage, it should be replaced or repaired by a qualified electrician before use.
- Wait until the bulb is completely cool before touching or removing it.
- Never use the SP160 lamp outside in a wet environment.
- Never move the appliance by pulling the cord. Make sure the cords do not come in contact with halogen bulb. Do not wind the cord around the appliance.
- Stand the SP160 on a flat surface only to prevent toppling.
- Do not touch the metal parts on the lamp while in use, these metal parts will become very hot.

Softbox Assembly:



1. Pictured is the SP4" lamp ring connector shown with the large end of the flex rod inserted.



2. Small end of flex rod fit into corner pocket on the softbox tent.



3. With three rods inserted into the ring and corners, fold the SP 4" ring into the tent.



4. Next insert the fourth rod into the SP 4" ring. *Note:* Keep the velcro flaps at the ring open to allow sufficient slack.



5. Insert the forth rod into the pocket on the velcro strap.



6. Push the velcro strap into place just below the lip of the tent. *Note:* the rods take a good deal of force to flex into position.



7. Now close the velcro flaps as shown in the picture.



8. The SP 4" ring can now be attached to the SP 160 flash unit. *DO NOT* over tighten.



9. Next attach the inner diffusion lense with the velcro straps.



10. Attach the outer diffusion lense to velcro patches on the outer edges.

Technical Notes for the electronic radio trigger device:

The SP160 Flash Kit is shipped with the DRT-2G electronic radio flash triggering device for your convenience.

It is an easy to use device that will give you extra control in the photographic studio environment. The DRT-2G is designed to work with a variety of flash units.

We provide a wide range of sync cord adaptors to fit most popular brands.

The DRT-2G trigger has two channels and uses a 23A battery (installed). The DRT-2G receiver uses two AAA batteries (not included).

1. To use the DRT-2G trigger device, first slide the trigger into the hot shoe found on top on your camera. If a hot shoe is not available, use the sync cord attachment found on the side of the trigger device.



2. Attach the receiver to a remote flash unit. Use the proper sync cord adaptor provided, plug into sync cord socket.

3. Switch the receiver unit ON/OFF button to the on position. Press the test button located on the top of the trigger unit. You will see a twinkling of the LED on the receiver unit. This indicates the trigger is working properly and is locked-in on a working channel of the receiver.



4. Switch the remote flash unit power switch to the on position with the DRT-2G receiver attached. Push the test button on the DRT-2G trigger, it should trigger the remote flash unit.

5. To change channels on the DRT-2G trigger, slide the channel switch on the side of the trigger device to the opposite position. Next press the power switch on the receive unit twice to reset the receiver.

For ordering spare bulbs or replacement parts, contact us at info@squareperfect.com. Also check out our extended line of photo equipment.



www.squareperfect.com